



Waterproof DS18B20 Sensor Kit

SKU:KIT0021



INTRODUCTION

If you are familiar with our product, you will find there is waterproof temperature sensor named DS18B20. This waterproof temperature sensor kit is using the same probe——DS18B20 probe AS . It contains a probe with a resistor module. So it is easy to connect on the Arduino board.

The DS18B20 temperature sensor provides 9 to 12-bit (configurable) temperature readings over a 1-Wire interface, so that only one wire (and ground) needs to be connected from a central microprocessor. Compatible with 3.0-5.5V systems.

Check 27 Pcs Sensor Kit for Arduino to get more sensors for arduino.

SPECIFICATION

- Operating voltage: 3.0~ 5.5V
- $\pm 0.5^{\circ}\text{C}$ Accuracy from -10°C to $+85^{\circ}\text{C}$
- Usable temperature range: -55 to 125°C (-67°F to $+257^{\circ}\text{F}$)
- 9 to 12 bit selectable resolution
- Uses 1-Wire interface- requires only one digital pin for communication
- Unique 64 bit ID burned into chip
- Multiple sensors can share one pin
- Temperature-limit alarm system
- Query time is less than 750ms
- 3 wires interface:
 - **Type A**
 - Red wire - VCC
 - Black wire - GND
 - Yellow wire - DATA
 - **Type B**
 - Red wire - VCC
 - Yellow wire - GND
 - Green wire - DATA
- Stainless steel tube 6mm diameter by 35mm(1.34") long
- Cable diameter: 4mm(0.16")
- Length: 90cm(35.43")

SHIPPING LIST

- Waterproof DS18B20 Digital temperature sensor (DFR0198) x1
- Terminal sensor adapter (DFR0055) x1
- Digital sensor cable (FIT0011)