

## Datasheet for 76650-0064

General Information				
Part Number:	76650-0064			
Manufacturer:	Molex / Waldom			
Title:	.062" Power Connector Kit			
Description:	Panel Mount Plug and Receptacle, 3 Circuit			
Product Family:	Standard .062"			
Certificates:	(Molex parts within this kit) - EU and China RoHS, UL, CSA and TUV			
Country of Origin:	Kit assembled in U.S.A.			
Specifications				

Design Wire to Wire **Configuration:** Pitch: 3.68mm (.145 ") Plug and Receptacle **Connector Type:** Mounting **Orientation:** Panel Mount **Circuit Sizes:** 3 **Current Rating:** 5 Amps Voltage: 250 Volts Wire size: 24-18 AWG

**Product Highlights** 

The Standard .062" is a durable and economical power or signal connector, capable of carrying up to 5.0 amps per circuit. Tough Nylon housings and robust terminal design create a durable, long lasting product. The Standard .062" products are reliable and offer high value in features and price. These products are an excellent choice for power or signal interconnect applications.

Features and Benefits	Applications
<ul> <li>Male and female terminals may be used in either plug or receptacle housings</li> <li>Free hanging or panel mount housing version available</li> <li>Round terminals may be oriented in any direction for fast assembly</li> <li>Passive (friction lock)</li> </ul>	<ul> <li>Power Supplies</li> <li>Appliances</li> <li>Gaming Machines</li> <li>Vending Machines</li> <li>Refrigerators</li> <li>Washing Machines</li> <li>Copy Machines</li> </ul>



## Datasheet for 76650-0064

## Bill of Materials for Part No. 76650-0064

Molex Part No.	Country of Origin	Description	Quantity in Kit
02-06-1103	USA	.062" Dia. Female Crimp Terminals, 24-18 AWG	11
02-06-2103	USA	.062" Dia. Crimp Type Male Pin Terminals, 24-18 AWG	11
03-06-1038	USA	3-Circuit Panel Mount Nylon Connector Receptacle	3
03-06-2033	USA	3-Circuit Panel Mount Nylon Connector Plug	3

## Recommended Molex Tool(s) for Part No. 76650-0064\*

Molex Part No.	Country of Origin	Description
63811-1000 *	Sweden	Hand Crimp Tool
11-03-0002 *	Sweden	Extraction Tool
11-02-0001 *	Sweden	Insertion Tool

\*Tools not included in kit. Tools ordered separately.